



PROBUS 087x0

All-in-one POS terminal

- ✓ 15" or 18.5" LCD display with Projected Capacitive Touch Panel
- ✓ Competitive cost model with Intel® Celeron® N3060
- ✓ High-performance models with Intel® Core i5-6500TE
- Slim housing & compact footprint design
- ✓ Stylish modern design
- Fanless
- Robust Aluminum Alloy (die-casting) housing and stand
- Easy maintenance-Quickly disassembly of POS terminal and stand
- ✓ Various POS peripherals for all requirements
- ✓ IP65 protection for front panel housing

PROBUS 087x0 series hardware destined to be either POS Terminal or Panel PC, casts modern existence for its 15" or 18.5" true flat touch panel and streamlining shape. No matter which role it plays, PROBUS 087x0 series was born with a fanless system without boring noise that makes it perfectly fit to a variety of locations. In case it is placed in harsh environment, PROBUS 087x0 series incorporates die casting technology to its stand so as to give carefree utilization.









PROBUS 087x0



All-in-one POS Terminal

Specification	PROBUS 08750	PROBUS 08760	PROBUS 08770	PROBUS 08780
Motherboard				
Processor	Intel® Celeron® Processor N3060	Intel® Celeron® Processor N3160	Intel® Core™ Processor i5-6500TE	Intel® Celeron® Processon N3160
System Memory	4GB, 1 x DDR3L (exp. up to 8GB) - 1600MHz (1.35V)	4GB, 1 x DDR3L (exp. up to 8GB) - 1600MHz (1.35V)	4GB, 1 x DDR4 (exp. up to 16GB) - 2133MHz (1.2V)	4GB, 1 x DDR3L (exp. up to 8GB) - 1600MHz (1.35V)
LCD Touch Panel				
LCD Size	15" LED LCD	18.5" LED LCD	18.5" LED LCD	15" LED LCD
Brightness			cd/m ²	
Resolution	1024 x 768	1366 x 768	1920 x 1080	1024 x 768
Touch Screen	Projected Capacitive with 10 touch points			
Tilt Adjustment		TE	3S	
Storage Device				
Hard Drive	64 GB SSD, expandable	64 GB SSD, expandable	256 GB SSD, expandable	64 GB SSD, expandable
Expansion				
Mini PCI-E Socket			1	
External I/O Ports				
USB Port	4 x USB (2 x USB 3.0, 2 x USB 2.0)	6 x USB (2 x USB 3.0, 4 x USB 2.0)	6 x USB (2 x USB 3.0, 4 x USB 2.0)	4 x USB (2 x USB 3.0, 2 x USB 2.0)
Serial Port	4 x COM ports RJ-45 cc	onnectors (2 ports with power	: 5V=green LED/12V=yellow	LED, enabled by BOIS)
Parallel Port	N/A			
LAN Port	1 x RJ-45 (10/100/1000Mbps Giga LAN)			
Second Display	1x HDMI (12V power by DC-jack, enabled in BIOS)			
Cash Drawer Port	1 x RJ-11 (12V/24V)			
DC Jack	1			
	1 x combo: mic & line out			
Audio Jack		1 x combo:	mic & line out	
Audio Jack Audio		1 x combo:	mic & line out	
	1 x 2W		mic & line out	1 x 2W
Audio	1 x 2W			1 x 2W
Audio Internal Speaker	1 x 2W Adapter (DC 65W,19V,3.42A)			
Audio Internal Speaker Power		2 x	2W	
Audio Internal Speaker Power Power Supply		2 x	2W	
Audio Internal Speaker Power Power Supply Control / Indicator		2 x	2W Adapter (DC 120W,19V,6.32A)	
Audio Internal Speaker Power Power Supply Control / Indicator Power Button		2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option)	
Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral		2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF	2W Adapter (DC 120W,19V,6.32A) 1	
Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral MSR		2 x Adapter (DC 90W,19V,4.74A) 3 Tracks MSF 1 (USB	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option)	
Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral MSR Finger print	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W,19V,4.74A) 3 Tracks MSF 1 (USB	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) tion	Adapter (DC 65W,19V,3.42A)
Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral MSR Finger print iButton	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W,19V,4.74A) 3 Tracks MSF 1 (USB Op	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) tion	Adapter (DC 65W,19V,3.42A)
Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral MSR Finger print iButton Second Display	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB Op or 10.1 , 14" or 15" Second L	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) tion	Adapter (DC 65W,19V,3.42A)
Audio Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral MSR Finger print iButton Second Display Certificate	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB 0p or 10.1 , 14" or 15" Second L FCC	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) i) (option) otion _CD Display with or without to C, CE	Adapter (DC 65W,19V,3.42A)
Audio Internal Speaker Power Power Supply Control / Indicator Power Button Peripheral MSR Finger print iButton Second Display Certificate EMC & Safety	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB 0p or 10.1 , 14" or 15" Second L FCC	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) otion _CD Display with or without to	Adapter (DC 65W,19V,3.42A)
Audio	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W,19V,4.74A) 3 Tracks MSf 1 (USB Op or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) i) (option) otion _CD Display with or without to C, CE	Adapter (DC 65W,19V,3.42A)
Audio	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB Op or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (-20°C to +80°C	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) 0) (option) 0) (option) 0 (option) 2CD Display with or without to 2, CE +32°F to +140°F)	Adapter (DC 65W,19V,3.42A
Audio	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W, 19V,4.74A) 3 Tracks MSF 1 (USB 0p or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (-20°C to +80°C 10% to 90% RF	Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) (option) CD Display with or without to C, CE +32°F to +140°F) (-4°F to +176°F)	Adapter (DC 65W,19V,3.42A)
Audio	Adapter (DC 65W,19V,3.42A)	2 x Adapter (DC 90W, 19V,4.74A) 3 Tracks MSF 1 (USB 0p or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (-20°C to +80°C 10% to 90% RF	Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) CD Display with or without to C, CE +32°F to +140°F) (-4°F to +176°F) 1 non-condensing	Adapter (DC 65W,19V,3.42A)
Audio	Adapter (DC 65W, 19V, 3.42A) Adapter (DC 65W, 19V, 3.42A) Adapter (DC 65W, 19V, 3.42A)	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB 0p or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (-20°C to +80°C 10% to 90% RH	2W Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) cD Display with or without to C, CE +32°F to +140°F) (-4°F to +176°F) 1 non-condensing 1 non-condensing	Adapter (DC 65W,19V,3.42A)
Audio	Adapter (DC 65W, 19V, 3.42A) Adapter (DC 65W, 3.42A) Adapter (DC 65W, 3.42A) Adapter (DC 65W, 3.42A) Adapter (DC 65W, 3.42A) Adapter	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB Op or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (-20°C to +80°C 10% to 90% RF 10% to 90% RF 10% to 90% RF 470 x 200 x 350 mm 6.9 kg	Adapter (DC 120W,19V,6.32A) 1 R USB (option) (option) (option) CD Display with or without to C, CE +32°F to +140°F) (-4°F to +176°F) 1 non-condensing 1 non-condensing 470 x 200 x 350 mm 6.9 kg	Adapter (DC 65W,19V,3.42A) ouch (option) 360 x 200 x 340 mm 5.6 kg
Audio	Adapter (DC 65W, 19V, 3.42A) Adapter (DC 65W, 3.42A) Adapter (DC 65W, 3.42A) Adapter (DC 65W, 3.42A) Adapter (DC 65W, 3.42A) Adapter	2 x Adapter (DC 90W, 19V, 4.74A) 3 Tracks MSF 1 (USB 0p or 10.1 , 14" or 15" Second L FCC 0°C to +60°C (-20°C to +80°C 10% to 90% RF 10% to 90% RF 470 x 200 x 350 mm	Adapter (DC 120W,19V,6.32A) Adapter (DC 120W,19V,6.32A) 1 R USB (option) b) (option) cD Display with or without to C, CE +32°F to +140°F) c (-4°F to +176°F) 1 non-condensing 1 non-condensing 470 x 200 x 350 mm 6.9 kg ESA mounting hole for panel	Adapter (DC 65W,19V,3.42A) ouch (option) 360 x 200 x 340 mm 5.6 kg

Rev. date: 11.09.2017