## **Smart App Professional Tower Series**

PR1000/1500ELCD

PRTBD0012EU-00

# **Extended Power Protection** for Mission-Criticals

Cyber Power®

The Professional Tower Series UPS provides advanced level of power protection to servers, telecom equipments, VOIP, internet working hardware and other mission-critical applications. Featuring Pure Sinewave output and Automatic Voltage Regulation (AVR) stabilizes the AC signal and maintains a safe voltage, it allows the UPS to maintain safe power levels for the connected equipment without resorting to battery power. Its detachable, remote-controllable Multifunction LCD Readout can be mounted on the wall or in the control center nearby to provide highest convenience and flexibility under different management


The optional SNMP/HTTP Remote Management Capability enables remote management and control of the system through standard web browser. Together with the included PowerPanel® Business Edition management software, it could provide corporate servers and critical workstations comprehensive network power management including unattended-shutdown, event logging, reporting, and notifications.


### **Applications**

- Home and Home Office
- Home Theater System
- Small Office
- Networking, Servers & Workstations

#### Series Features

- GreenPower UPSTM Technology
- Pure Sine Wave Output
- Line-Interactive UPS Topology
- Automatic Voltage Regulator (AVR)
- EMI, RFI, Surge and Lightning Spike Protection
- Critical Load Outlets
- Auto-Restart/Auto-Charge
- Emergency Power Off (EPO) Port
- Multifunction LCD Readout
- USB & Serial Connectivity Ports
- User-Replaceable Batteries
- SNMP/HTTP Remote Management Capability (Optional)
- PowerPanel® Business Edition Software





Back

**Energy-Saving** 

**Pure Sine Wave** 


**EPO Port** 

SNMP /HTTP

LCD Display

Detachable LCD

#### **Pure Sine Wave Output**



For applications that require Pure Sine Wave power, CyberPower provides UPS models with True Sine Wave output, also known as Pure Sine Wave. They are designed for electronic devices that have Power Factor Correction (PFC) Power Supplies as well as for small AC motors and other devices that need true sinewave power in order to function properly.

## PowerPanel® Business Edition Management S/W



**AUTO-SHUTDOWN SOFTWARE** CyberPower PowerPanel® Business Edition Management

Software, is compatible with Windows7, Vista, XP, 2000 Pro., ME. 98. Windows Server 2008. 2003, Mac and Linux.

\*Software functions may vary due to firmware version and/or hardware constraints.

# Smart App Professional Tower Series PR1000/1500ELCD

# Technical Specification



Model	PR1000ELCD	PR1500ELCD	
Configuration			
Capacity (VA / Watts)	1000/900	1500/1350	
Energy-Saving Technology	Yes		
Input			
Frequency Range	47 Hz - 63 Hz (Auto Sensing)		
Input Plug Type	IEC 320 C14		
Output			
UPS Outlets (Numbers)	(8) IEC		
On Battery Output Voltage	Pure Sine Wave at 230 Vac +/- 5%		
On Battery Output Frequency	50/60Hz +/- 1%		
Overload Protection	Circuit Breaker / Internal Current Limiting		
AVR	Double Boost, Single Buck		
Surge Protection and Filtering			
Surge Protection	Yes		
Physical			
Dimensions (H x W x D) (mm)	221 x 170 x 432		
Weight (kg)	18.9	25.1	
Battery			
Sealed Maintenance Free Lead Acid Battery	12V/12AH x 2	12V/17AH x 2	
User Replaceable	Yes		
Typical Recharge Time	8 Hours		
Runtimes			
Half-load / Full-load (mins)	8/24	8/25	
Status Indicators			
Indicators	Power On, Line Mode, On Battery, Fault, Replace Battery, LCD Display		
Audible Alarms	Battery Discharge, Battery Low, Fault, Overload		
Multi-function LCD Readout	Yes		
Communication			
PowerPanel® Business Edition	Windows 7 / Vista / XP / 2000, Server 2003 / 2008, Linux		
Management			
Self Test	Yes		
Auto-Charge / Auto-Restart	Yes		
Connectivity Ports	USB, Serial		
SNMP/HTTP Capable	Optional		
•	ithout notice @2012 CyberPower Systems All Trademarks are the property of their owners		

#All specifications are subject to change without notice. ©2012 CyberPower Systems. All Trademarks are the property of their owners.

## **Packaging Content**

• Main Unit

• User Manual

Software CD-ROM

• EPO Cable

• USB A+B Type Cable

• Serial Cable (DB-9) x 1

• IEC I/P Power Cord x 1

• Function Setup Guide x 1





DISTRIBUTED BY:









